

TECHNICAL CHARACTERISTICS INSTRUCTIONS FOR USE, ASSEMBLY INSTRUCTIONS, MAINTENANCE INSTRUCTIONS



MODEL 20-P

MANUALLY OPERATED VALVE WITH THERMOELECTRIC FLAME SUPERVISION AND ADJUSTABLE MECHANICAL THERMOSTAT

		CE
	EN 126:2012 EN 13611:2007 + A2:2011	
	models	20-P

Model 20P	Revision 00 – giu 16	page 1 of 7
-----------	----------------------	-------------



GENERAL INSTRUCTIONS


Feature	Description
Type	adjustable mechanical thermostat
Applications	ovens
types of gas used	1 st – 2 nd – 3 rd family
group	1
thermoelectric flame supervisor class	B (10,000 cicles)
number of outlets	1
nominal diameter	8
maximum working pressure	6.5 kPa
minimum working temperature (body)	0°C
maximum working temperature (body)	80/130°C
nominal flow rate (except inlet variants 15-15N-16-16N)	0.303 m ³ /h (test gas: air - pressure drop 100 Pa - EN 126-2012)
reduced flow rate (except inlet variants 15-15N-16-16N)	0.063 m ³ /h (test gas: air - pressure drop 100 Pa - EN 126-2012)
nominal flow rate (inlet variants 15-15N-16-16N)	0.140 m ³ /h (test gas: air - pressure drop 100 Pa - EN 126-2012)
reduced flow rate (inlet variants 15-15N-16-16N)	0.05 m ³ /h (test gas: air - pressure drop 100 Pa - EN 126-2012)
opening angle of max. flow rate	231°
opening angle of min. flow rate	52°
external leak tightness	leakage ≤ 60 cc/h (1 ml/min) (air - pressure 15 kPa)
internal leak tightness	leakage ≤ 20 cc/h (0.3 ml/min) (air - pressure 15 kPa)
gas valve continued operation	10,000 cycles (EN 126:2012 - EN 13611:2007 + A2:2011)
Flame supervisor device continued operation	10,000 cycles (EN 126:2012 - EN 13611:2007 + A2:2011)
inlet gas connection	bracket, flange (see attached sheets)
outlet gas connection	see attached sheets
storage temperature range	-15°C to + 50°C
hold-on current/drop-out current	≤ 180 mA / ≥ 60 mA (version 1)
(safety device)	≤ 110 mA / ≥ 20 mA (version 2)
	\leq 60 mA / \geq 10 mA (version 3)
Themocouples maximum closing time	90 sec
sensor's maximum temperature (bulb)	315 °C
temperature adjustment range	100 – 315°C
temperature tolerance	<u>+</u> 10°C
assembly position	Any position
Range of modulation	30°C
operating torque	≤ 30 N
mechanical differential	8°A
Temperature variation (130°C)	17°C
Drift for thermal overload	±5°C

These valves can be used with pipes of various diameters and flat manifolds.

To ensure a perfect seal, place an elastomer gasket between the manifold and the valve.

Gaskets of different materials can be used for the manifold depending on the temperature reached: silicon elastomer gaskets are resistant up to 130°C (all colors except black) while nitrile elastomer gaskets are resistant up to 80°C (black gasket).

Model 20P	Revision 00 – giu 16	page 2 of 7	





INSTRUCTIONS FOR USE

At 0°A the control shaft can be pressed completely to open the safety valve and allow the gas to flow through the pilot outlet. Few seconds after the pilot burner ignites, the thermocouple generates enough current to hold the safety magnet open. The control shaft needs no longer be pressed down.

In all the other allowed rotations isn't possible to open the safety valve and consequently hold on the magnet.

In this position (0°A) the thermostat (main burner outlet) is closed.

If the flame at the pilot outlet should accidentally go out, the thermocouple cools and the current is reduced, the safety magnet is closed and the flow of gas to the pilot outlet is blocked after few seconds.

Holding down and turning the control shaft anti-clockwise allows the gas to pass to the main burner. Once the thermostat has been turned through 52°A, gas begins to flow giving the minimum adjustable temperature. The thermostat can be turned through 231°A giving a continuous increase in temperature. Temperatures may be adjusted from 100°C to 315°C.

The thermostat has an adjustable perforated metering screw (by-pass) which fixes the reduced flow-rate at a preset value when fully tightened. If a different type of gas is used, the amount of reduced flow can be adjusted by turning the by-pass with a screwdriver. The thermostat can be equipped with one or more microswitches, which are firmly fastened by means of a metal staff. The microswitches are activated by simply pushing the spindle inward (microswitch used to activate the electric ignition) or by rotation of the spindle (microswitches used to perform other functions) – see table 1.

The pilot can't be turned off by the thermostat; the pilot's turning off must be realised by an external device.

TABLE 1 - MICROSWITCH CHARACTERISTICS		
Nominal tension 250 V		
Method for operation	push-button	
Max. operating temperature	125 °C	
Contact distance small – standard		
Protection level	IP00	
Insulation class	I	
Pollution situation standard		
Heat-resistance	category D	
Tracking index PTI250		

ASSEMBLY INSTRUCTIONS

The thermostats are designed to be used inside the cooking appliances, protected from any possible infiltrations of liquid or dirt and from the atmospheric agents. The non-observance of this prescription can compromise the correct working and the safety of the product.

The thermostats are designed to be used with manifolds of different diameters using flange or bracket fastenings.

To ensure a perfect seal, place an elastomer gasket between the manifold and the valve.


The outlet is designed for a connection pipe to the burner.

Calibration is determined in the factory and should not be altered even by qualified personnel. In case of irregularity, the whole thermostat should be replaced.

To avoid damage that may compromise correct functioning of the thermostats, do not exceed the tightening torques listed in the attached tables.

To avoid dirt or other material entering the equipment which may affect functioning and safety of the thermostat, a suitable filter should be mounted on the manifold supply inlet.

Model 20P	Revision 00 – giu 16	page 3 of 7
1110401 201	itoriololi oo gia io	page c c





MAINTENANCE INSTRUCTIONS

Maintenance of the taps is not foreseen, in case of failure or incorrect operation replace the tap with a new one (same model and same characteristics).

NB.: Leak test should be performed using a suitable appliance. Leak test mustn't be done by means of a flame or immersion of the valve in water or other liquids. The non-observance of this prescription can compromise the correct working and the safety of the product.



VARIANTS

INLET VARIANTS

Inlet	denomina	ation	asse	embly	
1 – 1N	single bracket	1 screw	tube diameter 14 mm	(hole diameter	8.2 mm)
2 – 2N	single bracket	1 screw	tube diameter 16 mm	(hole diameter	8.2 mm)
5 – 5N	single bracket	1 screw	tube diameter 18 mm	(hole diameter	8.2 mm)
8 – 8N	bracket	2 screws	tube diameter 18 mm	(hole diameter	8.2 mm)
9 – 9N	bracket	2 screws	tube diameter ½"gas	(hole diameter	8.2 mm)
13 – 13N	bracket	2 screws	tube diameter 16 mm	(hole diameter	8.2 mm)
15 – 15N	bracket	2 screws	tube diameter 8 mm	(hole diameter	5.7 mm)
16 – 16N	bracket	2 screws	tube diameter 10 mm	(hole diameter	5.7 mm)
17 – 17N	bracket	2 screws	tube diameter 14 mm	(hole diameter	8.2 mm)
19 – 19N	bracket	2 screws	tube diameter 19 mm	(hole diameter	8.2 mm)
20 – 20N	bracket	2 screws	tube diameter 17 mm	(hole diameter	8.2 mm)

OUTLET VARIANTS

Outlet	denomination	assembly
Α	tube diameter 6 mm	compression fitting
В	tube diameter 8 mm	compression fitting
С	tube diameter 10 mm	compression fitting
D	tube diameter 6 mm	compression fitting
Е	tube diameter 8 mm	compression fitting
F	G 3/8"	flared tube
G	G 1/4"	flared tube
Н	M 14 x 1.5	flared tube
L	tube diameter 9.525 mm	compression fitting
M	tube diameter 7 mm	compression fitting
N	tube diameter 8 mm	compression fitting
0	tube diameter 6.35 mm	compression fitting
S	tube diameter 6.35 mm	compression fitting
Т	tube diameter 10 mm	compression fitting
X	tube diameter 7 mm	compression fitting
Z	tube diameter 4 mm	compression fitting

PILOT OUTLET VARIANTS (p version)

outlet	denomination	assembly
Α	tube diameter 3.175 mm (1/8")	compression fitting
В	tube diameter 4 mm	compression fitting
С	tube diameter 4.76 mm (3/16")	compression fitting
D	tube diameter 6 mm	compression fitting
Е	tube diameter 6.35 mm (1/4")	compression fitting
F	tube diameter 3.5 mm	compression fitting
G	tube diameter 3.175 mm (1/8")	compression fitting
Н	tube diameter 4 mm	compression fitting
I	tube diameter 4.76 mm (3/16")	compression fitting
L	tube diameter 6 mm	compression fitting
M	tube diameter 6.35 mm (1/4")	compression fitting
N	tube diameter 3.5 mm	compression fitting
0	tube diameter 3.175 mm (1/8")	compression fitting
R	tube diameter 4 mm	compression fitting
S	tube diameter 4.76 mm	compression fitting
X	tube diameter 3.5 mm	compression fitting

Model 20P	Revision 00 – giu 16	page 5 of 7
1110401 201	i i i i i i i i i i i i i i i i i i i	page c c. r



Maximum torque values:

Maximum torque value			
Component	Nm	lbf.in	
Nut + olive + aluminium tube for oven outlet of thermostats	15	133	
Nut + olive + copper tube for oven outlet of thermostats	15	133	
Nut + olive + steel tube for oven outlet of thermostats	10	89	
Nut + tapered aluminium tube (bundy) for oven outlet of thermostats	15	133	
Nut + boulged aluminium tube for oven outlet of thermostats	15	133	
Nut for fixing thermocouple to magnet	4	35	
Screws for brackets	1.5	13	



MANUFACTURING DATE CODES

MONTH	CODE
JANUARY	N
FEBRUARY	0
MARCH	P
APRIL	R
MAY	S
JUNE	Т
JULY	U
AUGUST	V
SEPTEMBER	W
OCTOBER	X
NOVEMBER	Υ
DECEMBER	Z

YEAR	CODE	
1992	A	
1993	В	
1994	С	
1995	D	
1996	Е	
1997	F	
1998	Н	
1999	I	
2000	J	
2001	K	
2002	L	
2003	M	
2004	4	
2005 2006	5	
2006	6	
2007	7	
2008	8	
2009	9	
2010	0	
2011	1	
2012	2	
2013	3	
2014	4	
2015	5	
2016	6	

EXAMPLE: A COMPONENT PRODUCED IN APRIL 2004 IS MARKED

R4

Alternatively, on the component can be marked a four digit code indicating the week (first two digits) and the year of production (last two digits).

EXAMPLE: A COMPONENT PRODUCED THE 14TH WEEK OF 2004 IS MARKED

1404

Alternatively, on the component can be marked the day (first digits), the month (according with the code in table above) and the year of production (last two digits).

EXAMPLE: A COMPONENT PRODUCED IN APRIL, 19 2004 IS MARKED

19 R 04

Model 20P	Revision 00 – giu 16	page 7 of 7
1110401 201	i i i i i i i i i i i i i i i i i i i	pago i oi i